3D printing from Makerware

These are guidelines I use for printing PLA on a makerbot R2 and using an SD card to print from.

Save from solidworks as an STL file with the options needs.... - look at website link

Open Makerware



S Untitled.thing File Edit View MakerBots Services Help Upload Firm [+] 🔳 🕹 ۵F ? Onboard Preferenc Type of MakerBot No Connected MakerBo The Replicator 2 The Replicator 2X The Replicator (Dual) 5 The Replicator Thing-O-Matio ÷ \odot $\overline{\ }$ POWERED BY | (1) MakerBot The Replicator 2 📋 🖸 📵 🖬 😪 e 🌆 🔽 🗊 🤞 🐻

Select what model of makerbot you are going to print onto

Add (import) your part (stl model) into makerware by clicking on the add icon in makerware



Navigate to the file

			_
	[+] ጠ 土		
	Add Make Save		
Select objects			
Computer	► USB (F:) ► 3D print spikes	 ✓ Search 3D print spikes 	٩
Organize 🔻 New folder		= - 1 @	
Downloads	Name	Date modified Type	
Recent Places	🔮 spikes for 3D printing 6.3mm.STL	28/10/2014 10:54 stl_auto_file	
	spikes for 3D printing.STL	28/10/2014 09:33 stl_auto_file	
	🙍 spikes for 3D printing.thing	28/10/2014 09:43 thing_auto_file	
Documents			
Videos E			
i videos			
Computer			
Local Disk (C:)			
SD Disk (E:)			
🕳 USB (F:)			
File nam	spikes for 3D printing 6.3mm.STL	 All supported formats (*.obj *.s' 	
1		Open Cancel	

Move the part to the platform



When the object is selected double click on the turn icon so you can rotate the part so it has miminal support material and is positioned for the best printing outcome



After you've rotated it. Move the part to sit on the platform so the printer doesn't think the object is in mid air



Next we're going to export the file for printing. Select 'Make' icon



Depending on the quality you select different options but make sure you select print preview so you can see how long it will take and get an overview of how it will print

	AUTO MISI			
(? ×		
I want to:	Make It Now	Export to a File		
Export For:	The Replicator 2	•		
Material:	MakerBot PLA	▼		
Resolution:	🔘 Low (Faster)	Raft: 📝		
	Standard	Supports: 🔽		
	O High (Slower)			
Advar	nced Options			
Profile:	Standard	•		
Slicer:	MakerBot Slicer			
	Quality Tempe	erature Speed		
	Infill:	10%		
	Number of Shells:	2		
	Layer Height:	0.20 mm 🚖		
	Use Defaults	Create Profile		
Preview before printing				
Cancel		Export!		

Check the temperature. For PLA the temperature can vary even from different filaments of PLA. We use 220 to print green PLA and this works nicely. This might be too hot for most PLA filaments but it works for out free PLA we have in the lab.

•)	S ×		
	I want to:	Make It Now Export to a File		
	Export For:	The Replicator 2		
	Material:	MakerBot PLA 🔻		
	Resolution:	🔘 Low (Faster) Raft: 🔽		
		Standard Supports: ▼		
		e High (Slower) *		
	Advan	ced Options		
	Profile:	(High 🔹		
	Slicer:	MakerBot Slicer		
		Quality Temperature Speed		
		Extruder: 22þ °C		
		Use Defaults Create Profile		
	Cancel	Export!		
_				

Select export. When you do you'll see a slicing exporting loading bar processing the part for printing



Print preview

spikes for 3D printing 6.3mm.STL*	Company for	_ 0 X
File Edit View MakerBots Services Help		
File Edit View MakesBots Services Help File File File Help File File File Help File File Help Help <	Toolpath Visualization View from top Layer 106 Source and the second s	EDD
HATHATA	Are you happy with this preview? Export:	
POWERED BY (1) MakerBot		The Replicator 2
🚳 🤅 🚞 🖸 📵 🖻		🧤 💟 🗊 🐗 🍬 11:13 28/10/2014

Export	ter ► USB (F:) ►	✓ [€] → Search USB (F	× ()			
Organize New fold Image: Second Places Image: Second Places Image: Second Places Image: Second Places	Arre Name 3D print spikes attempt after 1446 catch up presentation Print V6 button half 2-220GREEN.x3g button half 2-230ABS.x3g	Date modified 28/10/2014 10:54 27/10/2014 14:46 05/06/2013 10:06 27/10/2014 18:51 27/10/2014 19:57 27/10/2014 20:22	Type File folder File folder File folder File folder X3G File X3G File			
Computer Coal Disk (C:) USB (F:)	<					
File name: spik Save as type: X3G,	es for 3D printing 6 SD print for firmware 7.0 or later (*.x3g)	Save	▼ ▼ Cancel			

Then select export and save the file to the SD card to put into the printer